



WEILA

BeiDou Positioning Module

WKG0254T02Y01

User Manual

DISCLAIMER

The data contained in this manual are derived from laboratory testing by Guangdong Weila Intelligent Technology Co., Ltd. and are for reference purposes only. Actual results may vary.

Guangdong Weila Intelligent Technology Co., Ltd. assumes no responsibility or liability for any use of the information contained herein, including but not limited to any direct or indirect damages, infringements, or losses arising from such use. No warranties, either express or implied, are made with respect to the contents of this manual.

Guangdong Weila Intelligent Technology Co., Ltd. reserves the right to modify or update the contents of this manual at any time without prior notice, in accordance with product version changes and actual conditions.

All trademarks, registered trademarks, and other intellectual property rights referenced in this manual are the property of their respective owners. Unauthorized use of such intellectual property is strictly prohibited.

Guangdong Weila Intelligent Technology Co., Ltd. reserves the right of final interpretation of this manual.

Table of Contents

| | |
|--|------|
| 1. Functional Description | 4th |
| 1.1. Overview | 4th |
| 1.2. Key Features | 4th |
| 1.3. Applications | 5th |
| 1.4. Assisted GNSS | 6th |
| 1.5. Output Protocol | 6th |
| 1.6. Performance Specifications | 6th |
| 2. Product Description | 7th |
| 2.1. Module Appearance | 7th |
| 2.2. Dimensions | 8th |
| 2.3. Pin Definition | 8th |
| 3. Electrical Characteristics | 9th |
| 3.1. Absolute Maximum Ratings | 9th |
| 3.2. Operating Conditions | 9th |
| 4. NMEA Protocol | 10th |
| 4.1. NMEA Protocol Characteristics | 10th |
| 4.2. Frame Structure | 10th |
| 4.3. NMEA Identifiers | 11th |
| 4.4. Support Messages | 12th |
| 5. Contact Us | 14th |

1. Functional Description

1.1. Overview

WKG0254T02Y01 is a high-performance single-constellation BeiDou positioning and navigation module with a compact size of 28 × 28 × 7 mm. It is based on the AT6668B-6N22 SoC, a sixth-generation multi-system GNSS single-chip solution from Zhongke Micro, supporting BeiDou-2 and BeiDou-3 (B1I and B1C) signals.

Leveraging proprietary fast acquisition technology, WKG0254T02Y01 can quickly capture a large number of visible satellites, enabling fast and accurate positioning. It significantly improves positioning performance in challenging environments such as urban canyons. The module integrates a high-performance embedded CPU, supporting a maximum position update rate of up to 10 Hz, making it suitable for high-dynamic applications sensitive to positioning latency. It also features dedicated anti-interference hardware acceleration circuitry, capable of rapidly detecting and suppressing RF interference.

With advantages including high sensitivity, low power consumption, and cost-effectiveness, WKG0254T02Y01 is ideal for applications such as vehicle navigation, handheld positioning devices, and automotive rearview mirrors.

Built on a new-generation integrated navigation SoC architecture, the module supports high-precision positioning and timing applications, while offering high integration, high performance, low power consumption, and compact size. It is widely applicable in automotive navigation, wearable devices, smartphones, IoT devices, and UAV (drone) applications.

1.2. Key Features

- Supports BDS-2 / BDS-3 (B1I, B1C)
- Support B1I / B1C standalone positioning
- Supports A-BDS
- Cold start sensitivity: -148 dBm
- Hot start sensitivity: -156 dBm
- Reacquisition sensitivity: -160 dBm
- Tracking sensitivity: -162 dBm
- Position accuracy: 2m (CEP50)
- TTFF: ≤23s
- Operating Current: ≤ 42 mA
- Standby Current: ≤ 10 μA
- Integrated LNA
- Built-in 25x25x4mm ceramic antenna(customization size available)
- Fast hot start (<1s) with onboard capacitor
- Standard NMEA-0183 output

1.3. Applications

- Vehicle navigation and tracking
- Power timing / 4G/5G synchronization
- IoT positioning devices
- UAV (drones)
- Portable devices

1.4. Assisted GNSS

Supports A-BDS, providing assistance data such as ephemeris, approximate position, and time.

This significantly reduces Time-To-First-Fix (TTFF), even in weak signal environments.

1.5. Output Protocol


The module outputs data via UART interface using NMEA-0183 protocol.

1.6. Performance Specifications

| Parameter | Specification |
|------------------------------------|----------------------|
| Signal Reception | BDS-2 / BDS-3 |
| Band | BDS:B1I、 B1C |
| Cold Start TTFF | ≤23s |
| Hot Start TTFF | ≤1s |
| Reacquisition TTFF | ≤1s |
| Cold Start Acquisition Sensitivity | -148dBm |
| Hot Start Acquisition Sensitivity | -156dBm |
| Reacquisition Sensitivity | -160dBm |
| Tracking Sensitivity | -162dBm |
| Positioning Accuracy | ≤2m(CEP50) |
| Velocity Accuracy | ≤0.1m/s (1σ) |
| Update Rate | 1Hz (max 10Hz) |
| Baud Rate | 115200 bps (default) |
| Interface Protocol | NMEA0183 |
| Power Supply | 3.3V – 5.5V |
| Power Consumption | ~42mA @5V |
| Operating Temperature | -40°C to +85 °C |
| Storage Temperature | -50°C to +125°C |
| Dimensions | 28x28x7mm |

2. Product Description

2.1. Module Appearance




Top



Bottom

- The front side of the module features an 25x25x4mm ceramic antenna (customization sizes available).
- The back side of the module is equipped with a 21.3x13.5x2mm shielding cover.
- A supercapacitor is integrated on the back side to provide backup power for the internal chip, ensuring fast positioning during hot start.
- 1PPS LED indicator (flashes after positioning fix)
- The back side includes a 5-pin 1.25 mm connector (pin from left to right: GND, RX, TX, 5V, 1PPS), and is also compatible with a 4-pin 1.25 mm connector (without 1PPS), as well as 5-pin solder pads (pin from left to right: GND, RX, TX, 5V, GND).

2.2. Dimensions



- The dimensions is 28x28x7mm
- The connector pad pitch is 1.25 mm
- The solder pad pitch is 2.0 mm
- The ceramic antenna dimensions are 25x25x4mm
- The shielding cover dimensions are 21.3x13.5x2mm
- The opening radius of the shielding cover is 2.2 mm

2.3. Pin Definition

| Pin | Type | Description |
|------|------|------------------------|
| 5V | P | Power supply, 3.0-5.5V |
| TX | IO | UART/TTL output |
| RT | IO | UART/TTLinput |
| 1PPS | IO | 1PPS Output |
| GND | P | Ground |

3. Electrical Characteristics

3.1. Absolute Maximum Ratings

| Parameter | Symbol | Min | Max | Unit |
|---------------------------|------------|------|------|------|
| Voltage | VDD | -0.3 | 5.5 | V |
| Digital I/O Voltage Level | Tx/Rx/1PPS | -0.3 | 4.1 | V |
| ESD Protection (HBM) | VESD(HBM) | - | 2000 | V |
| Operating Temperature | Topr | -40 | 85 | °C |
| Storage Temperature | Tstg | -50 | 125 | °C |

3.2. Operating Conditions

| Parameter | Symbol | Min | Typ | Max | Unit |
|-----------------------------------|---------------|------|-----|-----|------|
| Supply Voltage | VDD | 3.0 | 5 | 5.5 | V |
| Input Voltage | Vil | -0.3 | - | 0.6 | V |
| | Vih | 2.7 | - | 3.6 | V |
| Output Voltage | Vol(io=-12mA) | - | - | 0.4 | V |
| | Voh(io=12mA) | 2.8 | | 3.3 | V |
| Antenna Protection Current (Auto) | Io @VDD=5V | - | 42 | - | mA |
| Average Operating Current | Topr | -40 | - | 85 | °C |

4. NMEA Protocol

4.1. NMEA Protocol Characteristics

WKG0254T02Y01 BeiDou module complies with the international standard NMEA 0183 protocol, as well as a proprietary binary protocol.

The module outputs positioning data such as longitude, latitude, and time via the NMEA 0183 protocol. The proprietary binary protocol is used for module configuration, including parameters such as update rate, baud rate, etc.

Data is transmitted via an asynchronous serial interface. The transmission format consists of a start bit, followed by data bits. The data bits are transmitted in least significant bit (LSB) first order.

Data transmission format:

| | | | | | | | | | |
|-----------|----|----|----|----|----|----|----|----|----------|
| Start Bit | D0 | D1 | D2 | D3 | D4 | D5 | D6 | D7 | Stop Bit |
|-----------|----|----|----|----|----|----|----|----|----------|

Data Transmission Parameters:

| | |
|-----------------|-------------------|
| Baud Rate (bps) | Default 115200bps |
| Data Bits | 8bits |
| Stop Bit | 1 bits |
| Parity Bit | / |

4.2. Frame Structure

| NMEA Frame Structure | | | | |
|--------------------------------|--|---|---|----------------------------------|
| | Checksum Calculation Range | | | |
| \$ | <Address > | {, <Data >} | *<Checksum > | <CR><LF> |
| Start Delimiter | Address Field | Data Field | Checksum Field | End Sequence |
| Each sentence begins with '\$' | Consists of two parts: Talker ID and Sentence Type | As <input checked="" type="checkbox"/> Begins, contains variable-length or fixed-length data fields | XOR result of all characters between '\$' and '*', represented in hexadecimal | Each sentence ends with <CR><LF> |

4.3. NMEA Identifiers

NMEA distinguishes different GNSS modes by transmitting different talker IDs, as shown below:

| System | ID |
|-------------------------|----|
| BDS | BD |
| GPS SBAS QZSS | GP |
| GLONASS | GL |
| GNSS | GN |
| Proprietary Information | P |

4.4. Support Messages

WKG0254T02Y01 BeiDou module supports the following message fields. When multi-GNSS positioning is used, the talker identifier “GN” is applied; otherwise, a single-system identifier is used.

An overview of the supported NMEA messages is as follows:

| Message | Class/ID | Description |
|---------------------------|-----------|---|
| NMEA Standard Message | | Standard Message |
| GGA | 0x4E 0x00 | Receiver Position Data |
| GLL | 0x4E 0x01 | Geographic Position – Latitude / Longitude |
| GSA | 0x4E 0x02 | Dilution of Precision (DOP) and Active Satellites |
| GSV | 0x4E 0x03 | Satellites in View |
| RMC | 0x4E 0x04 | Recommended Minimum Specific GNSS Data |
| VTG | 0x4E 0x05 | Speed Over Ground and Course Over Ground |
| GST | 0x4E 0x07 | Receiver Pseudorange Error Statistics |
| ZDA | 0x4E 0x08 | Time and Date |
| ANT | 0x4E 0x11 | Antenna Status |
| LPS | 0x4E 0x12 | GNSS System Leap Second Correction Information |
| DHV | 0x4E 0x13 | Receiver Velocity Information |
| UTC | 0x4E 0x16 | Receiver Status and Simplified Leap Second Correction Information |
| NMEA Proprietary Messages | | Proprietary Messages |
| CAS00 | - | Save Configuration Parameters |
| CAS01 | - | Communication Protocol and UART Configuration |
| CAS02 | - | Set Positioning Update Rate |
| CAS03 | - | Enable or Disable Message Output and Configure Output Frequency |
| CAS04 | - | Set System Initialization and Channel Configuration |
| CAS05 | - | Set NMEA Talker Identifier |
| CAS06 | - | Query Module Software and Hardware Information |
| CAS10 | - | Startup Mode and Assisted Data Configuration |
| CAS12 | - | Standby Mode Control |
| CAS20 | - | Firmware Upgrade Command (OTA Supported) |

Among all supported NMEA messages, RMC is the most commonly used. It provides essential information including longitude, latitude, UTC time, and positioning status.

The TXT message provides additional information such as manufacturer identification, software and hardware versions, firmware release date, and antenna status (open, connected, or short circuit).

5. Contact Us

Company: Guangdong Weila Intelligent Technology Co., Ltd

TEL: 13602688458 (Mr. Zeng)

Email: sales@weikengtech.com

ADD: Floor 11, Block A, Building 9, Baoneng Science and Technology Park,
Qingxiang Road, Longhua District, Shenzhen

